

EB4000



- Dual voltage power with premium features and GFCI (Ground Fault Circuit Interrupter) protection on duplex receptacles.
- 4000 watts maximum AC output
- Industrial applications and Commercial usage
- Suitable for rental applications



SPECIFICATIONS

MAXIMUM AC OUTPUT (WATTS)	4000	BATTERY	N/A
AC Voltage Available	120/240	Approximate Running Time/Tankful (hrs)	10.1**/16.0****
MAXIMUM CONTINUOUS AC OUTPUT (WATTS)	3,500 5,000 (iAVR)	Rated Fuel Consumption (Litres/Hour)	2.32**
Max. Rated AC Amperage @ 120 V/240 V	29.2/14.6 (41.7/20.8 for 10 sec. iAVR)	Noise Level dB(A) (1.5 m to 7 m)	71**
GROUND FAULT CIRCUIT INTERRUPTER (GFCI)	Standard	Length (Without Handles and Wheels)	681 mm (26.8 in.)
FREQUENCY (HERTZ)	60	Length (With Handles and Wheels)	1,043 mm (41.1 in.)
AUTOMATIC VOLTAGE REGULATOR	Standard iAVR (Intelligent Automatic Voltage Regulator)	Width (Without Handles and Wheels)	530 mm (20.9 in.)
DC Output Volts/Amps	N/A	Width (With Handles and Wheels)	706 mm (27.8 in.)
Engine Type	Honda iGX270T2 OHV, 4-stroke, air-cooled	Height (Without Lift-Hook)	719 mm (28.3 in.)
DISPLACEMENT	270 cc	Height (With Lift-Hook)	773 mm (30.4 in.) standard
STARTING SYSTEM	Manual recoil	DRY WEIGHT	83.4 kg (183.9 lb.)
Low Level Oil Alert System	Standard	COLD CLIMATE TECHNOLOGY	Standard
AUTO THROTTLE	Standard	Common Duplex Receptacle Specifications	29.2 amps/120 VAC continuous is available as combined total from these twin duplex AC receptacles. Maximum of 14.6 amps available from each GFCI duplex receptacle.
REMOTE START CAPABILITY	No	DC Charging Cable	-
FUEL TANK CAPACITY (LITRES)	23.5	High Capacity 120/240 VAC Twist Lock Receptacle Specs	This receptacle will supply 29.2 amps at 120 VAC continuously. This receptacle will supply 14.6 amps (3.5 kVA) at 240 VAC continuously.
TRANSPORT WHEELS	2 Wheel standard	Distributor's Warranty (commercial use)	36-month
LIFTING HOOK	Standard	Distributor's Warranty (non-commercial use)	36-month

Models and/or colours may not be exactly as shown. Errors and omissions excepted. Specifications are subject to change without notice.

See your Honda Power Equipment dealer for details.

For optimum performance and safety, please read your owner's manual before operating your Honda product. Always wear the appropriate safety gear when operating your Honda.

©/TM — Trademarks of Honda Canada Inc. or used under licence from Honda Motor Co., Ltd. or third parties.